

## Description

Mi-Wave's 922 Series Harmonic Mixers with Diplexers

## Notes

Diplexer mixer port and mixer should be connected using the sma male to male adapter supplied or a short cable that is low in loss up to 12 GHz. Conversion loss will vary depending upon LO frequency and LO power level. \*\*\* Recommended for use with harmonic number less than 14\*\*\*\*\*

S/N: .

## Electrical Specifications

	Minimal	Typical	Maximum
RF Frequency	40 GHz		60 GHz
LO Frequency option 1	4 GHz		20 GHz
LO Frequency option 2	6 GHz		20 GHz
IF Frequency option 1	DC		3 GHz
IF Frequency option 2	DC		5 GHz
LO Power			+13 dBm
LO Plus RF Power Level			+13 dBm
Conversion Loss Depending upon LO Drive and LO Frequency		TBD	
RF Power Level			0 dBm

## Physical Specifications

RF Port	WR-19 Waveguide, UG-383/U-M Flange
LO Port	SMA(F)
IF input	SMA(F)
Material	Brass
Finish	Gold Plated
Diplexer	INCLUDED



Tested by: LS

Date: 2021-06-23

