

Description

Mi-Wave's 411 Series waveguide to coax transitions allow an efficient method of adapting from rectangular waveguide to a coaxial connector.

Notes

S/N: F2H113 G2H114

Electrical Specifications

	Minimal	Typical	Maximum
Frequency	33 GHz		50 GHz
Insertion Loss		0.7 dB	
Return Loss		17 dB typical	
Power Handling			15 W (CW)

Physical Specifications

Waveguide port	WR-22 Waveguide, UG-383/U Flange
Coaxial Port	1.85mm Female connector
Material	Aluminum
Finish	Gold Plated
Configuration	End Launch/In-Line Type

Tested by: Jon Kiernan

Date: 2024-01-18

