

## Description

Mi-Wave's 411 Series waveguide to coax transitions allow an efficient method of adapting from rectangular waveguide to a coaxial connector.

## Notes

090922SAC

S/N: FAH11Z GAH11E HAH113

## Electrical Specifications

	Minimal	Typical	Maximum
Frequency	33 GHz		50 GHz
Insertion Loss		0.7 dB	
Return Loss		20 dB typical	
Power Handling			15 W (CW)

## Physical Specifications

Waveguide port	WR-22 Waveguide, UG-383/U Flange
Coaxial Port	2.4mm Female connector
Material	Aluminum
Finish	Gold Plated
Configuration	End Launch/In-Line Type

Tested by: Kim Madden

Date: 2024-01-23

