

Description

Mi-Wave's 922 Series Harmonic Mixers with Diplexers

Notes

Diplexer mixer port and mixer should be connected using the sma male to male adapter supplied or a short cable that is low in loss up to 12 GHz. Conversion loss will vary depending upon LO frequency and LO power level. *** Recommended for use with harmonic number less than 14*****

S/N: N/A

Electrical Specifications

	Minimal	Typical	Maximum
RF Frequency	26.5 GHz		40 GHz
LO Frequency option 1	4 GHz		20 GHz
LO Frequency option 2	6 GHz		20 GHz
IF Frequency Option 1	DC		3 GHz
IF Frequency Option 2	DC		5 GHz
LO Power			+13 dBm
LO Plus RF Power Level			+13 dBm
Conversion Loss Depending upon LO Drive and LO Frequency		TBD	
RF Power Level			0 dBm

Physical Specifications

RF Port	WR-28 Waveguide, UG-599/U Flange
LO Port	SMA(F)
IF input	SMA(F)
Material	Brass
Finish	Gold Plated
Diplexer	INCLUDED



Tested by: LS

Date: 2021-02-15

